

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

SINTLY

Specifications

Specification	Value
No./teeth	11 qty
Power	1.4 kW
No./mount. holes [qty.]	2 qty
O.1 [mm]	98 mm
No./mount. holes with thread [qty.]	0 qty
C.1 [mm]	10.50 mm
L.1 [mm]	211 mm
Voltage	12 V
Rotation	CW
C.2 [mm]	10.50 mm
Size B [mm]	22 mm

Applications

Make
MAZDA

Original Code

19042	LFG1-18-400
M000T36371	MOT36371

Equivalent Code (Vehicle Manufacturer)

PRSE076 (3EFFE)	STRE076 (3EFFE)
AZMT-53-010-1405 (A.Z. MEISTERTEILE)	AC-CBS1493 (ACAUTO)
CGB-20408R (AINDE)	10438602 (ALANKO)
UD102599S (AS-PL)	SMI231 (AUTOTEAM)
0986024760 (BOSCH)	S103386 (BTS TURBO)
S103628 (BTS TURBO)	115599 (CARGO)
F032115599 (CARGO)	CST35231GS (CASCO)
9946 (CEVAM)	DRS0408 (DELCO)
324057112 (DRI)	STR5227 (ELECTROLOG)
25-3457 (ELSTOCK)	11040964 (EUROTEC)
CS1493 (HC PARTS)	3111554 (HENKEL PARTS)
J5213053 (HERTH+BUSS)	803-11032 (IAP QUALITY PARTS)
10035231OV (ITAB AUTOMOTIVE)	EST-4512 (KAVO PARTS)
STM0408 (KRAUF)	254781 (KUHNER)
254781M (KUHNER)	722600/M (KUTNAK AUTOMOTIVE)
336599 (LOGISTIK)	LRS02286 (LUCAS)
LRS2286 (LUCAS)	LFG1-18-400 (MAZDA)
4732003 (NK)	88214182 (POWERMAX)
IR1231 (PROTECH)	140.534.112.130 (PSH)
140.534.112.370 (PSH)	140.534.112.460 (PSH)
S130.179 (PSH)	S145.034 (PSH)
20437132OE (REAL)	6035231.1 (SANDO)
STX210218R (STARDAX)	ST01488 (TMI)
460401 (VALEO)	19042N (WAI / TRANSP0)
91-27-3420 (WILSON)	STR71300 (WOODAUTO)
WOOSTR71300 (WOODAUTO)	