



产品规格

规格	参数值
No./mount. holes [qty.]	3 qty
O.1 [mm]	89 mm
No./mount. holes with thread [qty.]	0 qty
L.1 [mm]	339 mm
Rotation	CW
Size A [mm]	89 mm
Size B [mm]	45 mm
No./teeth	10 qty
Power	2.8 kW
O.3 [mm]	127 mm
O.2 [mm]	89 mm
C.1 [mm]	11.00 mm
Voltage	12 V
C.3 [mm]	11.00 mm
C.2 [mm]	11.00 mm

适用车型

品牌
FORD

原厂编码

10465151	10465314
6585	F3HZ11001B

替代编码 (汽车制造商)

0-23000-2230 (NIKKO)	0-23000-2234 (NIKKO)
0-23000-2380 (NIKKO)	0-23000-2440 (NIKKO)
0-23000-2444 (NIKKO)	0-23000-2480 (NIKKO)
0-24000-3200 (NIKKO)	112253 (CARGO)
F032112253 (CARGO)	140-28102 (ROBERT'S)
254216 (KUHNER)	35259630 (PRESTOLITE)
3675172RX (CUMMINS)	3924410 (CUMMINS)
3935071 (CUMMINS)	50-8425 (WAI / TRANSPO)
6585N (WAI / TRANSPO)	6585R (WAI / TRANSPO)
6060115 (SANDO)	6585 (LESTER)
CST60115 (CASCO)	CST60115AS (CASCO)
CST60115ES (CASCO)	CST60115GS (CASCO)
CST60115OS (CASCO)	CST60115RS (CASCO)
F3HT11001DB (FORD)	F3HT11001DC (FORD)
F3HZ11001B (FORD)	F3HZ11002B (FORD)
F4HT11001BA (FORD)	F7HT11001FA (FORD)
F7HT11002FH (FORD)	MAV621150 (SIOM)
STR80109 (WOODAUTO)	STRS626 (3EFFE)
TS-1625 (DIXIE)	S1059 (AS-PL)
UD02203S (AS-PL)	339807 (LOGISTIK)
STR2651 (ELECTROLOG)	3134772 (VOLVO)